

Capacitor Basics

Capacitance

| |
|--|
| Definition: Capacitance (C) is the ability of a component to store an electrical charge. |
| Unit: Farad (F) |
| Formula: $C = Q / V$ |
| Where: <ul style="list-style-type: none">C is the capacitance in FaradsQ is the charge in CoulombsV is the voltage in Volts |
| Typical Values: Ranging from picofarads (pF) to millifarads (mF). |
| Energy Stored: The energy (E) stored in a capacitor is given by $E = 0.5 * C * V^2$ |

Capacitor Construction

| | |
|-------------------------|---|
| Basic Structure: | Two conductive plates separated by a dielectric material. |
| Dielectric: | The dielectric material affects capacitance and voltage rating. Common materials include ceramic, plastic film, and electrolytic solutions. |
| Lead Types: | Axial (leads on either end) and radial (leads on the same end). |

Key Parameters

| | |
|--|--|
| Voltage Rating: | Maximum voltage that can be safely applied to the capacitor. |
| Tolerance: | The allowable deviation from the specified capacitance value (e.g., ±10%). |
| Temperature Coefficient: | Change in capacitance per degree Celsius (°C). |
| ESR (Equivalent Series Resistance): | Represents the internal resistance of the capacitor, affecting its performance in AC circuits. |

Capacitor Types

Ceramic Capacitors

| |
|--|
| Characteristics: Non-polarized, small size, low cost, good for high-frequency applications. |
| Applications: Decoupling, bypass, and filtering. |
| Types: Multilayer Ceramic Capacitors (MLCCs) are common. |

Electrolytic Capacitors

| | |
|-------------------------|--|
| Characteristics: | Polarized, high capacitance values, suitable for low-frequency applications. |
| Types: | Aluminum electrolytic and tantalum electrolytic. |
| Applications: | Power supply filtering, energy storage. |
| Polarity: | Must be connected with correct polarity to avoid damage. |

Film Capacitors

| |
|--|
| Characteristics: Non-polarized, good stability, low ESR, various dielectric materials (e.g., polyester, polypropylene). |
| Applications: Audio circuits, precision timing, high-frequency circuits. |
| Types: Polyester film, polypropylene film, etc. |

Other Capacitor Types

| | |
|---|---|
| Supercapacitors (Ultracapacitors): | Very high capacitance, used for energy storage in applications like electric vehicles and backup power systems. |
| Variable Capacitors: | Adjustable capacitance, used in tuning circuits. |

Capacitor Circuits

Series and Parallel Combinations

| | |
|-----------------------------|--|
| Series Capacitors: | Total capacitance is less than the smallest individual capacitance. $1/C_{total} = 1/C_1 + 1/C_2 + \dots + 1/C_n$ |
| Parallel Capacitors: | Total capacitance is the sum of individual capacitances. $C_{total} = C_1 + C_2 + \dots + C_n$ |

RC Circuits

| |
|---|
| Charging: The voltage across the capacitor increases exponentially when charging through a resistor. |
| Discharging: The voltage across the capacitor decreases exponentially when discharging through a resistor. |
| Time Constant (τ): $\tau = R * C$ (in seconds), where R is the resistance in ohms and C is the capacitance in farads. Represents the time it takes for the capacitor to charge or discharge to approximately 63.2% of its final value. |

Capacitive Reactance

| | |
|------------------------------|---|
| Definition: | Opposition to AC current flow, similar to resistance but frequency-dependent. |
| Formula: | $X_C = 1 / (2 * \pi * f * C)$ Where: <ul style="list-style-type: none">X_C is the capacitive reactance in ohmsf is the frequency in HertzC is the capacitance in Farads |
| Frequency Dependence: | Capacitive reactance decreases as frequency increases. |

Applications

| | |
|---------------------------|---|
| Filtering: | Blocking DC signals while allowing AC signals to pass (or vice versa). |
| Coupling: | Passing AC signals from one circuit to another while blocking DC bias. |
| Decoupling/Bypass: | Providing a local energy source for ICs, reducing noise on power supply lines. |
| Timing Circuits: | Using RC time constants for creating delays and setting frequencies in oscillators. |

Practical Considerations

Reading Capacitor Values

| | |
|-------------------------|---|
| Direct Marking: | Some capacitors have the capacitance value directly printed on them (e.g., 100nF, 4.7μF). |
| Code Systems: | Others use a code system (e.g., 104 = 10 x 10 ⁴ pF = 100nF). Last digit is multiplier (power of 10) in pF. |
| Tolerance Codes: | Letters indicate tolerance (e.g., K = ±10%, M = ±20%). |

Selecting the Right Capacitor

| | |
|------------------------------|---|
| Considerations: | Capacitance value, voltage rating, tolerance, temperature coefficient, ESR, size, and cost. |
| Application Specific: | Choose capacitor type based on the specific application requirements (e.g., ceramic for high frequency, electrolytic for high capacitance). |

Troubleshooting

| | |
|---------------------------|---|
| Testing: | Use a multimeter with capacitance measurement or an LCR meter to test capacitor values. |
| Common Failures: | Short circuits, open circuits, decreased capacitance, increased ESR. |
| Visual Inspection: | Check for bulging, leakage, or physical damage, especially in electrolytic capacitors. |

Safety Precautions

| | |
|------------------------|---|
| Discharge: | Always discharge capacitors before handling, especially high-voltage capacitors, to avoid electric shock. |
| Polarity: | Ensure correct polarity when using polarized capacitors. |
| Voltage Rating: | Never exceed the rated voltage of a capacitor. |